IR-FA SERIES FIBER OPTIC RADIATION THERMOMETER




The IR-FA series is a fiber optic radiation thermometer featuring multi-function and highspeed response.

Three types, single-color type for low temperature, single-color type for medium/high temperature and two-color type, are available.

IR-FA series realized usability and stable temperature measuring as digital temperature display and parameter setting functions, signal modulation and optional analog output are built in. Various options including lens assembly with finder, laser-spotting function, communications interface and analog input which enables emissivity external settings or automatic emissivity computation are available.




- Low temperature type with high-speed response (20ms) and short wavelength enables to measure objects with low emissivity like as metals.
- Medium/high temperature type with high accuracy (±0.5 to 1% for 1000 to 2000℃) and high-speed response (10ms) is for various temperature measurement fields.
- Two-color type is stable with less effectiveness of smoke, vapor, dust and lack-of-view.
- Temperature measuring of high speed movement material, inductive heating object, explosion-proof environment and vacuum equipment are applicable.
- Digital temperature display and parameter setting with key operation.
- Compact, light weight and DIN rail mounting.
- By using heat-resistive fiber optic, measuring in the environment at 150°C is possible without any watercooling.
- Stable temperature measuring is possible by signal modulation function.
- Laser function for easy spotting of measuring point (option).
- A lens assembly with finder for spotting of measuring point with eyes is available from accessories.
- Communications interface (RS485) enables data logging and parameter setting on a computer.
- Emissivity setting (emissivity ratio for two-color type)
 by analog input or automatic emissivity computation function is selectable. (option)
- CE conformed.






IR-FACR

■ STRUCTURE



■ MODELS





■ SPECIFICATIONS

	Low temperature	Medium/high temperature		Two color type		
Models	IR-FACR IR-FAI IR-FAS		IR-FAS	IR-FAQI IR-FAQS IR-FAQ		
Measuring system	Single color type Single color type		Two color	type		
Element	PbS (cooling type)	InGaAs	Si	InGaAs/InGaAs		
Wavelength	2.0μm	1.55μm	0.9 <i>μ</i> m		0.85/1.00μm 0.9/1.55μm	
Accuracy ratings	70°C to 300°C : ±4°C	Lower than 100		1100/ 1100/	(() ()	
$(\varepsilon = 1.0)$	300°C to 500°C: ±5°C	1000°C to 1500°C:±0.5% of measured value				
(*,	Higher than 500°C: ±1.0%					
	of measured value	1500°C to 2000°C: ±1.0% of measured value Higher than 2000°C: ±2% of measured value				
Repeatability	2°C or less	0.2°C	70 0. <u></u> 70 0	iourou vara		
Temperature drift	0.2°C/°C					
Resolution	70°C to 100°C: Approx 3°C 100°C to 200°C: Approx 2°C, Higher than 200°C: Approx 0.5°C	0.5℃		1.0°C	V	
Response time	20ms	10ms		40ms		
Emissivity (ratio) compensation	Set value: 1.999 to 0.050*1	Set value: 1.999	to 0.050	Ratio set v	/alue: 1.999 to 0.050	
Signal modulation	DELAY: Tracing of average value (smoo	•, ,				
	PEAK: Tracing of maximum value			ble), modula	tion ratio 0= peak hold	
Display Analog output	LCD 4 digit (Temperature displated to 20 mA DC isolated output (In	· · · · · · · · · · · · · · · · · · ·				
	Accuracy rating: ±0.2% of output range Output resolution: 0.04% of output range (IR-FAC), 0.01% of output range (except IR-FAC) Output scaling: Setting within measuring temperature range Dummy output: Setting within 0 to 100% of analog output					
Contact output	2 point selectable from high/low, high/high, low/low alarm or error signal Photo-coupler 30V DC, max.50mA					
Contact input	1 point, peak hold reset or samp	le hold, dry conta	act or open collec	tor		
Parameter setting by keys	Operator mode: Settings of emissivity, signal modulation, alarms, reference temperature input for automatic emissivity calculation, etc. Engineering mode: Settings of output scaling, zero-span, automatic emissivity calculation, output correction, optional function, etc. Operator mode: Setting of emissivity calculation, alarms, reference temperature input for automatic emissivity calculation, etc. Engineering mode: Settings of output scaling, zero-span, automatic emissivity calculation, output correction, optional function, etc.					
Computing function	Zero-span adjustment, automatic emissiv	·	tput correction		ustment, automatic emissivit on*2, output correction	
Self-diagnosis	Thermometer temperature abnormal	rmal, parameter	error			
Laser function*3	Semi-conductor laser unit built-in.			ot available	in high sensitivity type	
Analog input	Input signal: 4 to 20 mA DC Remote setting of emissivity or reference temperature input Input signal: 4 to 20 mA DC Remote setting of emissivity ratio of					
Communications IF	setting for automatic emissivity of RS485, transmitting of measured	·	decimal point) tra	automatic er	mperature input setting of missivity ratio calculation	
Working temperature	5 to 40 °C	0 to 50 °C	aconnai pointy, tra	monnung/16	boolving of parameters	
Rated power supply	24V DC (allowable voltage fluctu		to 28\/DC\			
Power consumption	Maximum 15VA	Maximum 3VA	10 20 V D C)			
Connection		IVIAXIIIIUIII 3VA				
	Cramp type no screw terminals	na				
Mounting Case material	DIN rail mounting or wall mounti					
	Steel	Plastic	SOmm About 250)a		
Dimensions, weight	W140 x H110 x D65mm, about 1.0kg				:tu , tu , \	
Standard sassassins	EMC directive: EN55011 Group		uo∠-∠ (^except hi	ign sensitiv	пу туре)	
Standard accessories	Slotted screwdriver, instruction r	nanual				

^{*1)} The compensation range is ε\(\frac{\pmathcap{1.0}}{2.0}\) to 0.8 for the measured temperature of 70 to 80°C and ε\(\frac{\pmathcap{1.0}}{2.0}\) to emissivity (ratio) is automatically computed by inputting the reference input temperature with key setting or analog input (option).

*3) For IR-FACR, when used in combination with lens assembly models IR-FL1, IR-FL2, IR-FL6, IR-FL8, combination of external laser spotting unit (IR-ZFX16) is recommended for laser spotting function.

■ Lens assembly / fiber optic

	Core 400 μm	Core 800 µm (only for low temperature)		
Fiber	Single core quartz			
Sheath	Without metallic prote	ctive tube		
	(heat resistive sheath,	/ glass wool braid)		
	With metallic protective	re tube		
	(heat resistive sheath/ glass w	vool braid + SUS flexible tube)		
Working temp.	0 to 150°C 0 to 50°C at measured			
	value of 70 to 120°C			
	0 to 80°C at measured			
	value of 120°C or higher			
Length	Refer to fiber length			
Allowable bending	R100mm	R150mm		
Connection	Connector			
Mounting	Screw mounting			
Accessories	Air purge case			
	Material: Aluminum			
	Air flow: 1 to 5NL/min	(clean air)		

■ Power supply unit IR-ZFEP

Output voltage	24V DC
Power supply	100 to 240V AC
	Universal power supply 50/60Hz
Output current	600mA
External dimensions	W45 x H75 x D96mm

■ Data logging software IR-VXF1(option)

Measured data logging by combination with IR-FA series radiation thermometer.

Model


IR-VXF1□

Language
J: Japanese
E: English


General specification

Operation	OS drive	Windows 2000/XP/Vista		
environment	Hard drive	Capacity: 20MB or more		
	Memory	256MB or more		
	Drive	CD-ROM drive		
	Interface	RS232C port 1pc		
Function	Digital display and trend display of measured			
	data			
	Data storing/replay(CSV type) and printing			
	Connecting unit: Maximum 3 units			

Unit structure




■ Example of use






DIMENSIONS

●General lens assembly (single code: IR-ZFL□)



Lens assembly type		0,1,2,3	4	5	6	7	8
Low temperature	L	35	15	10	10.5	8.5	45
	φD		7.5			7.8	7.5
Medium/high	L	35	15	10	10.5		45
temperature Two color type	ϕ D		7.5				7.5

● Air purge case (single code: IR-ZFX02)




Lens assembly type		0,1,2,3	4	5	6	7	8
Low temperature	L	10	30	35	34.5	36.5	0
Medium/high temperature Two color type	L	10	30	35	34.5		0


(Unit: mm)

Fiber length

● Fiber without metallic protection tube (Single code: IR-ZFH□□, IR-ZFJ02)




● Fiber with metallic protection tube (single code: IR-ZFN□□, IR-ZFK02)




Fiber length	Core 400μm	Core $800 \mu m$ (only for low temperature)	
Low temperature	2m, 4m, 5m	2m	
Medium/high temperature, two color type	2m, 4m, 5m, 10m, 15m, 20m	_	

■ Main unit dimensions

Medium/high temperature, two color type




Low temperature






ACCESSORIES


●Air purge hard case IR-ZFX05




● Hard case with radiation seal




Hard case with water-cooling radiation seal




●Water-cooling case IR-ZFX08




Opto-couple type protecting tube




Opto-couple type protecting tube IR-FTCH1 (for vacuum furnace)




Protecting case for electro-magnetic tube IR-ZFX09




● Protecting tube for continuous casting IR-ZFX10



Measuring window for vacuum furnace IR-ZFX11




●Vacuum flange



Optical fiber connector IR-ZFX13



■Lens assembly with finder IR-FF




Mirror adapter IR-ZFX04

Air purge case fixed screw hole (3-M3)

Measuring distance & measuring diameter

Type1 (ϕ 5 at 500)		Type2 (Type3 (ϕ 10 at 1000)		
Distance	Diameter	Distance	Diameter	Distance	Diameter	
L1:400	D1: φ7	L1:270	D1: φ7	L1: 800	D1: φ11	
L2:500	D2: φ 5	L2: 370	D2 : φ4	L2:1000	D2: φ10	
L3:600	D3 : φ 9	L3:470	D3 : φ 9	L3: 1200	D3 : φ15	

● Laser spotting unit IR-ZFX16 (Battery drive)



Specifications subject to change without notice. Printed in Japan (I) 2009. 4

CHINO CORPORATION

32-8 KUMANO-CHO,ITABASHI-KU,TOKYO 173-8632

Telephone: +81-3-3956-2171 Facsimile: +81-3-3956-0915 E-mail: inter@chino.co.jp Website: www.chino.co.jp/